### 74AC11000 QUADRUPLE 2-INPUT POSITIVE-NAND GATE

SCLS054A - APRIL 1987 - REVISED APRIL 1996

- Center-Pin V<sub>CC</sub> and GND Configurations Minimize High-Speed Switching Noise
- **EPIC** ™ (Enhanced-Performance Implanted CMOS) 1-µm Process
- 500-mA Typical Latch-Up Immunity at
- **Package Options Include Plastic** Small-Outline (D) Packages and Standard Plastic 300-mil DIPs (N)

#### **DORNPACKAGE** (TOP VIEW) 16**[**] 1B 1A 15 2A 1Y 2 2Y 🛮 3 14 🛮 2B GND [ 13 V<sub>CC</sub> GND [] 5 12 V<sub>CC</sub> 3Y 🛮 6 11 🛮 3A 10 3B 4Y 9 🛮 4A 4B

### description


This device contains four independent 2-input NAND gates. It performs the Boolean function  $Y = \overline{A} \cdot \overline{B}$  or  $Y = \overline{A} + \overline{B}$  in positive logic.

The 74AC11000 is characterized for operation from -40°C to 85°C.

**FUNCTION TABLE** (each gate)

INP	UTS	OUTPUT
Α	В	Υ
Н	Н	L
L	X	Н
Х	L	Н

## logic symbol†



<sup>†</sup> This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.




Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

EPIC is a trademark of Texas Instruments Incorporated.



SCLS054A - APRIL 1987 - REVISED APRIL 1996

### logic diagram (positive logic)



### absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

Supply voltage range, V <sub>CC</sub>	–0.5 V to 7 V
Input voltage range, V <sub>I</sub> (see Note 1)	0.5 V to V <sub>CC</sub> + 0.5 V
Output voltage range, V <sub>O</sub> (see Note 1)	$-0.5 \text{ V to V}_{CC} + 0.5 \text{ V}$
Input clamp current, $I_{IK}$ ( $V_I < 0$ or $V_I > V_{CC}$ )	±20 mA
Output clamp current, $I_{OK}$ ( $V_O < 0$ or $V_O > V_{CC}$ )	±50 mA
Continuous output current, $I_O(V_O = 0 \text{ to } V_{CC})$	±50 mA
Continuous current through V <sub>CC</sub> or GND	±100 mA
Maximum power dissipation at T <sub>A</sub> = 55°C (in still air) (see Note 2): D package	1.3 W
N package	1.1 W
Storage temperature range, T <sub>stq</sub>	

<sup>†</sup> Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.



NOTES: 1. The input and output voltage ratings may be exceeded if the input and output current ratings are observed.

<sup>2.</sup> The maximum package power dissipation is calculated using a junction temperature of 150 °C and a board trace length of 750 mils, except for the N package, which has a trace length of zero.

SCLS054A - APRIL 1987 - REVISED APRIL 1996

### recommended operating conditions

			MIN	NOM	MAX	UNIT	
VCC	Supply voltage		3	5	5.5	٧	
		V <sub>CC</sub> = 3 V	2.1				
$v_{\text{IH}}$	High-level input voltage	$V_{CC} = 4.5 \text{ V}$	3.15			V	
		$V_{CC} = 5.5 \text{ V}$	3.85				
		V <sub>CC</sub> = 3 V			0.9		
$v_{IL}$	Low-level input voltage	$V_{CC} = 4.5 \text{ V}$			1.35	٧	
		$V_{CC} = 5.5 \text{ V}$			1.65	]	
VI	Input voltage		0		VCC	V	
٧o	Output voltage		0		VCC	٧	
		V <sub>CC</sub> = 3 V			-4		
IОН	High-level output current	$V_{CC} = 4.5 \text{ V}$			-24	mA	
		$V_{CC} = 5.5 \text{ V}$			-24		
		V <sub>CC</sub> = 3 V			12		
loL	Low-level output current	$V_{CC} = 4.5 \text{ V}$			24	mA	
		$V_{CC} = 5.5 \text{ V}$			24		
Δt/Δν	Input transition rise or fall rate	-	0		10	ns/V	
TA	Operating free-air temperature		-40		85	°C	

# electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	V	T,	T <sub>A</sub> = 25°C			MAY	LINUT
PARAMETER	TEST CONDITIONS	Vcc	MIN	TYP	MAX	MIN	0.1 0.1 0.4 0.44 0.44 1.65 ±1	UNIT
		3 V	2.9			2.9		
	I <sub>OH</sub> = -50 μA		4.4			4.4		
		5.5 V	5.4			5.4		
$v_{OH}$	I <sub>OH</sub> = -4 mA	3 V	2.58			2.48		٧
		4.5 V	3.94			3.8		
	$I_{OH} = -24 \text{ mA}$	5.5 V	4.94			4.8		
	$I_{OH} = -75 \text{ mA}^{\dagger}$	5.5 V				3.85		
		3 V			0.1		0.1	
	I <sub>OL</sub> = 50 μA	4.5 V			0.1		0.1	
		5.5 V			0.1		0.1 0.1 0.44 0.44 1.65 ±1	
$v_{OL}$	I <sub>OL</sub> = 12 mA	3 V			0.36		0.44	V
	1- 24 mA	4.5 V			0.36		0.44	
	I <sub>OL</sub> = 24 mA	5.5 V			0.36		0.44	
	$I_{OL} = 75 \text{ mA}^{\dagger}$	5.5 V					1.65	
ΙĮ	V <sub>I</sub> = V <sub>CC</sub> or GND	5.5 V			±0.1		±1	μΑ
lcc	$V_I = V_{CC}$ or GND, $I_O = 0$	5.5 V			0.4		40	μΑ
Ci	V <sub>I</sub> = V <sub>CC</sub> or GND	5 V		3.5				pF

<sup>†</sup> Not more than one output should be tested at a time, and the duration of the test should not exceed 10 ms.



SCLS054A - APRIL 1987 - REVISED APRIL 1996

# switching characteristics over recommended operating free-air temperature range, $V_{CC}$ = 3.3 V $\pm$ 0.3 V (unless otherwise noted) (see Figure 1)

PARAMETER	FROM	то	T,	<sub>Δ</sub> = 25°C	;	MIN	MAX	UNIT
PARAMETER	(INPUT)	(OUTPUT)	MIN	TYP	MAX	IAIIIA	WAX	CINII
<sup>t</sup> PLH	A or B	V	1.5	7.2	9.8	1.5	11.1	20
t <sub>PHL</sub>	AOID	T T	1.5	5.8	8.6	1.5	9.6	ns


## switching characteristics over recommended operating free-air temperature range, $V_{CC}$ = 5 V $\pm$ 0.5 V (unless otherwise noted) (see Figure 1)

PARAMETER	FROM	то	T <sub>A</sub> = 25°C		MIN MA	мах	UNIT	
PARAIVIETER	(INPUT)	(OUTPUT)	MIN	TYP	MAX	IVIIIV	IVIAA	UNIT
t <sub>PLH</sub>	A or B	V	1.5	5	6.5	1.5	7.4	no
<sup>†</sup> PHL	AOID	T.	1.5	4.4	6.1	1.5	6.8	ns

### operating characteristics, V<sub>CC</sub> = 5 V, T<sub>A</sub> = 25°C

	PARAMETER	TEST CONDITIONS		TYP	UNIT
Cpd	Power dissipation capacitance per gate	$C_L = 50 pF$ ,	f = 1 MHz	33	pF

#### PARAMETER MEASUREMENT INFORMATION



NOTES: A. C<sub>L</sub> includes probe and jig capacitance.

- B. Input pulses are supplied by generators having the following characteristics: PRR  $\leq$  1 MHz,  $Z_O = 50 \ \Omega$ ,  $t_f = 3 \ ns$ ,  $t_f = 3 \ ns$ .
- C. The outputs are measured one at a time with one input transition per measurement.

Figure 1. Load Circuit and Voltage Waveforms



#### IMPORTANT NOTICE

Texas Instruments (TI) reserves the right to make changes to its products or to discontinue any semiconductor product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

TI warrants performance of its semiconductor products and related software to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

Certain applications using semiconductor products may involve potential risks of death, personal injury, or severe property or environmental damage ("Critical Applications").

TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, INTENDED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT APPLICATIONS, DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS.

Inclusion of TI products in such applications is understood to be fully at the risk of the customer. Use of TI products in such applications requires the written approval of an appropriate TI officer. Questions concerning potential risk applications should be directed to TI through a local SC sales office.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards should be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein. Nor does TI warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used.

Copyright @ 1996, Texas Instruments Incorporated